

NAG Fortran Library Routine Document

F04LHF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of ***bold italicised*** terms and other implementation-dependent details.

1 Purpose

F04LHF calculates the approximate solution of a set of real linear equations with multiple right-hand sides, $AX = B$ or $A^T X = B$, where A is an almost block-diagonal matrix which has been factorized by F01LHF.

2 Specification

```

SUBROUTINE F04LHF(TRANS, N, NBLOKS, BLKSTR, A, LENA, PIVOT, B, LDB, IR,
1                      IFAIL)
  INTEGER              N, NBLOKS, BLKSTR(3,NBLOKS), LENA, PIVOT(N), LDB, IR,
1                      IFAIL
  real                A(LENA), B(LDB,IR)
  CHARACTER*1          TRANS
```

3 Description

The routine solves a set of real linear equations $AX = B$ or $A^T X = B$, where A is almost block-diagonal. A must first be factorized by F01LHF. F04LHF then computes X by forward and backward substitution over the blocks.

4 References

Diaz J C, Fairweather G and Keast P (1983) Fortran packages for solving certain almost block diagonal linear systems by modified alternate row and column elimination *ACM Trans. Math. Software* **9** 358–375

5 Parameters

- 1: TRANS – CHARACTER*1 *Input*
On entry: TRANS specifies the equations to be solved as follows:
 if TRANS = 'N', solve $AX = B$;
 if TRANS = 'T', solve $A^T X = B$.
- 2: N – INTEGER *Input*
On entry: n , the order of the matrix A .
Constraint: $N > 0$.
- 3: NBLOKS – INTEGER *Input*
On entry: the total number of blocks of the matrix A , as supplied to F01LHF.
Constraint: $0 < \text{NBLOKS} \leq N$.
- 4: BLKSTR(3,NBLOKS) – INTEGER array *Input*
On entry: information which describes the block structure of A , as supplied to F01LHF.

- 5: A(LENA) – *real* array *Input*
On entry: the elements in the factorization of A , as returned by F01LHF.
- 6: LENA – INTEGER *Input*
On entry: the dimension of the array A as declared in the (sub)program from which F04LHF is called.
Constraint: $LENA \geq \sum_{k=1} \text{NBLOKSBLKSTR}(1, k) \times \text{BLKSTR}(2, k)$.
- 7: PIVOT(N) – INTEGER array *Input*
On entry: details of the interchanges in the factorization, as returned by F01LHF.
- 8: B(LDB,IR) – *real* array *Input/Output*
On entry: the n by r right-hand side matrix B .
On exit: B is overwritten by the n by r solution matrix X .
- 9: LDB – INTEGER *Input*
On entry: the first dimension of the array B as declared in the (sub)program from which F04LHF is called.
Constraint: $LDB \geq N$.
- 10: IR – INTEGER *Input*
On entry: r , the number of right-hand sides.
Constraint: $IR > 0$.
- 11: IFAIL – INTEGER *Input/Output*
On entry: IFAIL must be set to 0, -1 or 1. Users who are unfamiliar with this parameter should refer to Chapter P01 for details.
On exit: IFAIL = 0 unless the routine detects an error (see Section 6).
For environments where it might be inappropriate to halt program execution when an error is detected, the value -1 or 1 is recommended. If the output of error messages is undesirable, then the value 1 is recommended. Otherwise, for users not familiar with this parameter the recommended value is 0. **When the value -1 or 1 is used it is essential to test the value of IFAIL on exit.**

6 Error Indicators and Warnings

If on entry IFAIL = 0 or -1 , explanatory error messages are output on the current error message unit (as defined by X04AAF).

Errors or warnings detected by the routine:

IFAIL = 1

On entry, $N < 1$,
or NBLOKS < 1 ,
or $IR < 1$,
or $LDB < N$,
or $N < \text{NBLOKS}$,
or LENA is too small,
or illegal values detected in BLKSTR,
or $\text{TRANS} \neq \text{'N'}$ or 'T' .

7 Accuracy

The accuracy of the computed solution depends on the conditioning of the original matrix A .

8 Further Comments

None.

9 Example

To solve the set of linear equations $Ax = b$ where

$$A = \begin{pmatrix} -1.00 & -0.98 & -0.79 & -0.15 \\ -1.00 & -0.25 & -0.87 & 0.35 \\ & 0.78 & 0.31 & -0.85 \\ & -0.82 & 0.12 & -0.01 \\ & -0.83 & -0.98 & -0.58 \\ & -0.21 & -0.93 & -0.84 \\ & & 0.89 & -0.69 & -0.98 & -0.76 \\ & & & 0.78 & -0.93 & -0.76 & 0.48 \\ & & & -0.87 & -0.14 & -1.00 & -0.59 \\ & & & -0.93 & -0.91 & 0.10 & -0.89 \\ & & & & 0.85 & -0.39 & 0.79 \\ & & & & 0.17 & -1.37 & 1.29 \\ & & & & & & 1.10 \\ & & & & & & & -0.99 \\ & & & & & & & -0.87 \\ & & & & & & & -0.93 \\ & & & & & & & 0.85 \\ & & & & & & & 0.17 \\ & & & & & & & & 0.08 \\ & & & & & & & & -0.67 \\ & & & & & & & & -0.24 \\ & & & & & & & & & 0.54 \\ & & & & & & & & & 0.16 \\ & & & & & & & & & -0.46 \\ & & & & & & & & & 0.98 \\ & & & & & & & & & 0.70 \\ & & & & & & & & & 0.43 \\ & & & & & & & & & & 0.71 \\ & & & & & & & & & & -0.47 \\ & & & & & & & & & & -0.25 \\ & & & & & & & & & & 0.89 \end{pmatrix}$$

and

$$b = \begin{pmatrix} -2.92 \\ -1.17 \\ -1.30 \\ -1.17 \\ -2.10 \\ -4.51 \\ -1.71 \\ -4.59 \\ -4.19 \\ -0.93 \\ -3.31 \\ 0.52 \\ -0.12 \\ -0.05 \\ -0.98 \\ -2.07 \\ -2.73 \\ -1.95 \end{pmatrix}$$

The exact solution is

$$x = (1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1, 1)^T.$$

9.1 Program Text

Note: the listing of the example program presented below uses *bold italicised* terms to denote precision-dependent details. Please read the Users' Note for your implementation to check the interpretation of these terms. As explained in the Essential Introduction to this manual, the results produced may not be identical for all implementations.

```
*      F04LHF Example Program Text
*      Mark 14 Revised.  NAG Copyright 1989.
*      .. Parameters ..
      INTEGER                NIN, NOUT
      PARAMETER              (NIN=5,NOUT=6)
      INTEGER                NBLMAX, NMAX, IRLMAX, LENA, LDB
      PARAMETER              (NBLMAX=10,NMAX=20,IRLMAX=5,LENA=200,LDB=NMAX)
```

```

*      .. Local Scalars ..
      real TOL
      INTEGER I, IFAIL, INDEX, IR, J, K, N, NBASEK, NBLOKS
*      .. Local Arrays ..
      real A(LENA), B(LDB,IRMAX)
      INTEGER BLKSTR(3,NBLMAX), PIVOT(NMAX)
*      .. External Subroutines ..
      EXTERNAL F01LHF, F04LHF
*      .. Executable Statements ..
      WRITE (NOUT,*) 'F04LHF Example Program Results'
*      Skip heading in data file
      READ (NIN,*)
      READ (NIN,*) NBLOKS
      WRITE (NOUT,*)
      IF (NBLOKS.LE.NBLMAX) THEN
        NBASEK = 0
        N = 0
        DO 40 I = 1, NBLOKS
          READ (NIN,*) (BLKSTR(J,I),J=1,3)
          DO 20 K = 1, BLKSTR(1,I)
            IF (NBASEK+BLKSTR(2,I)*BLKSTR(1,I).GT.LENA) THEN
              WRITE (NOUT,*)
+              ' Array A is too small for this problem'
              STOP
            ELSE
              READ (NIN,*) (A(NBASEK+(J-1)*BLKSTR(1,I)+K),J=1,
+              BLKSTR(2,I))
            END IF
          20 CONTINUE
          NBASEK = NBASEK + BLKSTR(2,I)*BLKSTR(1,I)
          N = N + BLKSTR(1,I)
        40 CONTINUE
        IF (N.GT.NMAX) THEN
          WRITE (NOUT,*) ' N is too large'
          STOP
        END IF
        TOL = 0.0e0
        IFAIL = -1
*
*      CALL F01LHF(N,NBLOKS,BLKSTR,A,LENA,PIVOT,TOL,INDEX,IFAIL)
*
      IF (IFAIL.EQ.0) THEN
        READ (NIN,*) IR
        IF (IR.LE.IRMAX) THEN
          READ (NIN,*) ((B(I,J),I=1,N),J=1,IR)
          IFAIL = -1
*
*      CALL F04LHF('N',N,NBLOKS,BLKSTR,A,LENA,PIVOT,B,LDB,IR,
+      IFAIL)
*
      IF (IFAIL.EQ.0) THEN
        WRITE (NOUT,*) 'Component Solution'
        DO 60 I = 1, N
          WRITE (NOUT,99999) I, (B(I,J),J=1,IR)
        60 CONTINUE
      END IF
      ELSE
        WRITE (NOUT,*) ' Too many right hand sides speciûed'
      END IF
      END IF
      ELSE
        WRITE (NOUT,*) ' NBLOKS is invalid'
      END IF
      STOP
*
99999 FORMAT (1X,I5,6X,5F6.4)
      END

```

9.2 Program Data

F04LHF Example Program Data

```

5      : Number of blocks
2 4 3  : Number of rows, columns and column overlap, block 1
-1.00 -0.98 -0.79 -0.15
-1.00 0.25 -0.87 0.35      : End block 1
4 7 4  : Number of rows, columns and column overlap, block 2
0.78 0.31 -0.85 0.89 -0.69 -0.98 -0.76
-0.82 0.12 -0.01 0.75 0.32 -1.00 -0.53
-0.83 -0.98 -0.58 0.04 0.87 0.38 -1.00
-0.21 -0.93 -0.84 0.37 -0.94 -0.96 -1.00      : End block 2
5 8 2  : Number of rows, columns and column overlap, block 3
-0.99 -0.91 -0.28 0.90 0.78 -0.93 -0.76 0.48
-0.87 -0.14 -1.00 -0.59 -0.99 0.21 -0.73 -0.48
-0.93 -0.91 0.10 -0.89 -0.68 -0.09 -0.58 -0.21
0.85 -0.39 0.79 -0.71 0.39 -0.99 -0.12 -0.75
0.17 -1.37 1.29 -1.59 1.10 -1.63 -1.01 -0.27      : End block 3
3 6 3  : Number of rows, columns and column overlap, block 4
0.08 0.61 0.54 -0.41 0.16 -0.46
-0.67 0.56 -0.99 0.16 -0.16 0.98
-0.24 -0.41 0.40 -0.93 0.70 0.43      : End block 4
4 5 0  : Number of rows, columns and column overlap, block 5
0.71 -0.97 -0.60 -0.30 0.18
-0.47 -0.98 -0.73 0.07 0.04
-0.25 -0.92 -0.52 -0.46 -0.58
0.89 -0.94 -0.54 -1.00 -0.36      : End block 5
1      : Number of right hand sides
-2.92 -1.27 -1.30 -1.17 -2.10 -4.51 -1.71 -4.59
-4.19 -0.93 -3.31 0.52 -0.12 -0.05 -0.98 -2.07
-2.73 -1.95      : End right hand side 1

```

9.3 Program Results

F04LHF Example Program Results

Component Solution

```

1      1.0000
2      1.0000
3      1.0000
4      1.0000
5      1.0000
6      1.0000
7      1.0000
8      1.0000
9      1.0000
10     1.0000
11     1.0000
12     1.0000
13     1.0000
14     1.0000
15     1.0000
16     1.0000
17     1.0000
18     1.0000

```
