# NAG Fortran Library Routine Document F06PPF (DSYR)

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of **bold italicised** terms and other implementation-dependent details.

## 1 Purpose

F06PPF (DSYR) performs the symmetric rank-1 update operation

$$A \leftarrow \alpha x x^T + A$$

where A is an n by n real symmetric matrix, x is an n element real vector, and  $\alpha$  is a real scalar.

## 2 Specification

SUBROUTINE FO6PPF (UPLO, N, ALPHA, X, INCX, A, LDA)

INTEGER N, INCX, LDA

double precision
ALPHA, X(\*), A(LDA,\*)

CHARACTER\*1 UPLC

The routine may be called by its BLAS name dsyr.

### 3 Description

None.

#### 4 References

None.

#### 5 Parameters

1: UPLO – CHARACTER\*1

Input

On entry: specifies whether the upper or lower triangular part of A is stored as follows:

if UPLO = 'U', the upper triangular part of A is stored; if UPLO = 'L', the lower triangular part of A is stored.

Constraint: UPLO = 'U' or 'L'.

2: N – INTEGER Input

On entry: n, the order of the matrix A.

Constraint: N > 0.

3: ALPHA – double precision

Input

On entry: the scalar  $\alpha$ .

4: X(\*) – *double precision* array

Input

On entry: the vector x.

5: INCX – INTEGER

Input

On entry: the increment in the subscripts of X between successive elements of x.

*Constraint*: INCX  $\neq$  0.

[NP3657/21]

#### 6: A(LDA,\*) - double precision array

Input/Output

**Note**: the second dimension of the array A must be at least max(1, N).

On entry: the n by n symmetric matrix A. If UPLO = 'U', the upper triangle of A must be stored and the elements of the array below the diagonal are not referenced; if UPLO = 'L', the lower triangle of A must be stored and the elements of the array above the diagonal are not referenced.

On exit: the updated matrix A.

#### 7: LDA – INTEGER

Input

On entry: the first dimension of the array A as declared in the (sub)program from which F06PPF (DSYR) is called.

*Constraint*:  $LDA \ge max(1, N)$ .

## 6 Error Indicators and Warnings

None.